



## Standard Features

- 3 ft ArmorGuard cable included
- Capacities from 2,500 to 10,000 lb
- Non-Legal for Trade

## Specifications

**Safe Overload:**  
150%

**Full Scale Output:**  
3 mv/V nominal  
Output is standardized for each model of load bar, consult factory for details

**Maximum Excitation:**  
15 VDC

**Nonlinearity:**  
0.02% full scale

**Hysteresis:**  
0.02% full scale

**Bridge Resistance:**  
350 ohm

**Temperature:**  
-40 °F to 111 °F (-40 °C to 44 °C)

**Cable Configuration:**  
8 ft between bars, hard-wired  
12 ft cable with quick disconnect for the indicator

**Warranty:**  
Two-year limited

## Part Number/Price

Part #	Description	Est. Weight	Price
<b>2,500 lb Capacity</b>			
<b>152016</b>	2,500 lb 22 – Farm Bar set, with square pads	92 lb	Consult
<b>5,000 lb Capacity</b>			
<b>152018</b>	5,000 lb 26 – Farm Bar set, with square pads	111 lb	Consult
<b>152019</b>	5,000 lb 33 – Farm Bar set, with square pads	117 lb	Consult
<b>152020</b>	5,000 lb 36 – Farm Bar set, with square pads	122 lb	Consult
<b>152021</b>	5,000 lb 40 – Farm Bar set, with square pads	128 lb	Consult
<b>152022</b>	5,000 lb 44 – Farm Bar set, with square pads	134 lb	Consult
<b>152023</b>	5,000 lb 48 – Farm Bar set, with square pads	140 lb	Consult
<b>10,000 lb Capacity</b>			
<b>185437</b>	10,000 lb 32 – Farm Bar set, with square pads	146 lb	Consult
<b>152024</b>	10,000 lb 36 – Farm Bar set, with square pads	146 lb	Consult
<b>152025</b>	10,000 lb 48 – Farm Bar set, with square pads	169 lb	Consult
<b>152026</b>	10,000 lb 60 – Farm Bar set, with square pads	204 lb	Consult
<b>152027</b>	10,000 lb 72 – Farm Bar set, with square pads	224 lb	Consult

## Options/Accessories

Part #	Description	Price
<b>159788</b>	Extension cable, farm bar, 10 ft long	Consult
<b>127556</b>	Home run cable, 12 ft long, 4-pin male to blunt end, for indicator	Consult
<b>202711</b>	380 Universal Segmented LCD Display, Battery Powered	Consult
<b>23113</b>	Printer TM-U295	Consult
<b>71630</b>	Scale tickets, 500/pack	Consult
<b>15547</b>	Blunt end to DB25, RS-232 cable for printer to indicator	Consult
<b>206433</b>	Power supply, 12 V 6 W	Consult



PN 127556 Home-run cable

# Farm Bars

## Dimensions

### Dimensions

Farm Bar 2,500U				
A	B*	C	D*	E
22.00 in	15.00 in	19.75 in	25.75 in	4.00 in

Farm Bar 5,000U				
A	B*	C	D*	E
26.00 in	19.00 in	23.75 in	29.75 in	4.00 in
33.00 in	26.00 in	30.75 in	36.75 in	4.00 in
36.00 in	29.00 in	33.75 in	39.75 in	4.00 in
40.00 in	33.00 in	37.75 in	43.75 in	4.00 in
44.00 in	37.00 in	41.75 in	47.75 in	4.00 in
48.00 in	41.00 in	45.75 in	51.75 in	4.00 in

Farm Bar 10,000U				
A	B*	C	D*	E
32.00 in	25.00 in	29.75 in	35.75 in	4.00 in
36.00 in	29.00 in	33.75 in	39.75 in	4.00 in
48.00 in	41.00 in	45.75 in	51.75 in	4.00 in
60.00 in	53.00 in	57.75 in	63.75 in	4.00 in
72.00 in	65.00 in	69.75 in	75.75 in	4.00 in

\* B equals dimension A less 7 inches

\* D equals dimension C plus 6 inches

